



Representative Image

Catalog No. CR306C002

Description: SIZE 1 STARTER7

UPC No

Home > Starters > NEMA > Full Voltage Starters

- NEMA Rated Full Voltage Magnetic Starters.
- Three-Phase Magnetic Starters.
- Nonreversing.
- Non-combination.
- Open.
- NEMA Size 1 with Thermal Overload Relay.
- 600 Volts Maximum 50/60 Hertz. Continuous Amperage rating 27.

Descriptors

Category

Full Voltage Starters

by ABB